

DESCRIZIONE	CODICE	VALORI	N°	DESCRIZIONE	CODICE	VALORI	N°
I Bobina AF	PK56020 0		S 1	Cond ceram A3a	PK19602	50 pF	C 21
			S 2	" " mica A3a	PK19031	500 "	C 22
			C 6	" " ceram A3a	PK19005	100 "	C 23
			S 3	" " " A3a	PK19005	100 "	C 24
II Bobina AF	PK56021 0		S 4	" " " A3a	PK19602	50 "	C 25
			S 5	" " a carto B2a	PK20503	0.1 mF	C 26
			S 6	" " " B2a	PK20502	50000 pF	C 27
			C 8	" " " B2a	PK20502	50000 "	C 28
I Bobina oscillatore	PK56022 0		S 7	" " " B2a	PK20503	0.1 mF	C 29
			S 8	" " " B2a	PK20502	50000 pF	C 30
			C 9	" " " B2a	PK20502	50000 "	C 31
			S 9	" " " B2a	PK20502	50000 "	C 32
II Bobino oscilli	PK56023 0		S 10	" " " B2a	PK20502	50000 "	C 33
			S 11	" " " B5a	PK20521	1000 "	C 34
			S 12	" " " B5a	PK20526	5000 "	C 35
			C 11	" " " B2a	PK20505	64000 "	C 36
I Bobina MF	PK56024 0		S 13	" " " B2a	PK20523	5000 "	C 37
			S 14	" " " B2a	PK20530	25000 "	C 38
			C 16	" " " B2a	PK20502	50000 "	C 39
Bobina MF speciale	PK56025 0		S 15	" " " B2a	PK20531	3200 "	C 1
			C 18	" " Elett 450 V	SK18012	16 mF	C 2
			S 17	" " " 450 "	SK18012	16 "	C 3
II Bobina MF	PK56019 0		S 18	" " mica A2b + 2%	PK19023	4000 pF	C 4
			S 19	" " " A3a	PK19005	100 "	C 5
			C 19	" " " A3a	PK19005	100 "	C 6
			C 20	Resist carb 1 W	2877097	5000 ohm	R 1
Trasform d'uscita	PK50516 0		S 20	" " 0.25 "	2877365	320 "	R 2
			S 21	" " 0.25 "	2877399	0.8 Mohm	R 3
Bobina impedenza	A100032 0		S 22	" " 0.25 "	2877387	50000 ohm	R 4
Bob altop PK82016	2822051 1		S 23	" " 0.25 "	2877362	160 "	R 5
			S 24	" " 1 "	2877105	32000 "	R 6
Trasformatore alimen- tazione	PK51016 0		S 25	" " 1 "	2877106	40000 "	R 7
			S 26	" " 0.5 "	2877040	32000 "	R 8
			S 27	" " 1 "	2877095	3200 "	R 9
			S 28	" " 0.5 "	2877055	1 Mohm	R 10
I Bobina AF	PK56027 0		S 29	" " 1 "	2877107	50000 ohm	R 11
			S 30	" " 1 "	2877123	2 Mohm	R 12
			C 6	" " 0.5 "	2877055	1 "	R 13
I Bobina oscillatore	PK56028 0		S 7	" " 0.5 "	2877017	160 ohm	R 14
			S 8	" " 1 "	2877086	400 "	R 15
			S 9	" " 0.25 "	2877397	0.5 Mohm	R 16
Carpo altop. PK82018 0	PK56014 0		C 9	" " 0.25 "	2877397	0.5 "	R 17
Bobina mobile altop 5648	2822069 0		S 30	" " 0.25 "	2877398	0.64 "	R 18
" " " PK82018 0	2822043 1		S 25	" " 1 "	2877127	5 "	R 19
			S 25	" " 0.25 "	2877387	50000 ohm	R 20
Trasform. uscite	PK50515 0		S 20	Poten. carb. caselat a presa	PK80843	0.7 Mohm	R 21
			S 21	Resist. carb. 0.25 W	2877370	1000 ohm	R 22
			S 22	Poten. a carbone	PK80844	50000 "	R 23
Trasfor alimentaz	PK51017 0		S 23	Resist. carb. 0.25 W	2877372	1600 "	R 24
			S 26	" " 0.25 "	2877381	12300 "	R 25
			S 27	" " 0.25 "	2877380	10000 "	R 26
			S 28	" " 0.25 "	2877399	0.8 Mohm	R 27
Cond. elettr 350 V	SK18013	32 mF	S 29	" " 0.25 "	2877399	0.8 "	R 28
" " " 350 "	SK18013	32 "	C 1	" " 0.25 "	2877393	0.2 "	R 29
Cond el secco 25 "	2818224	25 "	C 2	Valvola	ECH3		L 1
Cond var doppio	2821252	11-490	C 3	" "	EF9		L 2
		11-490	C 4	" "	EF9		L 3
Compens ed ario	2821236 1	3-30 pF	C 5	" "	EBL1		L 4
" " " "	2821236 1	3-30 "	C 6	" "	AZI		L 5
Compens a filo	2821208	200 "	C 7	" "	EMI		L 6
Cond mica A2b + 2%	PK19024	400 "	C 8	Lomp illuminaz	PK91807 0	6.3V 0.15A	L 7
" " " A2b + 1%	PK19032	250 "	C 9	" "	PK91807 0	6.3V 0.15A	L 8
" " " A2b + 1%	PK19033	280 "	C 10				